

A Low-Voltage Current Mirror for Transconductance Amplifiers

Hamdi Ercan¹, Sezai Alper Tekin²

¹Erciyes University, Department of Avionics, Kayseri, Turkey

²Erciyes University, Department of Industrial Design Engineering, Kayseri, Turkey

Abstract: In this study, a low-voltage current mirror to use in differential pairs as an active load is introduced. The proposed current mirror which can operate at ± 0.5 V has high output impedance and low input impedance. The proposed structure employs the principle of voltage level-shifting for PMOS transistors. The voltage level-shifting operation has been achieved by using the bulk voltage at this structure. Spice simulations also justify this current mirror's outstanding performance with a bandwidth of 11 GHz using an external capacitor at an input current of 200 μ A.

Keywords: PMOS level shifter; low-voltage; current mirror; current-mode; differential pair; bulk voltage

Nizkonapetostno tokovno zrcalo za transkonduktančne ojačevalnike

Izveček: Članek predstavlja nizkonapetostno zrcalo za uporabo kot aktivno breme v diferencialnih parih. Predlagano zrcalo obratuje pri napetosti ± 0.5 V in ima visoko vhodno nizko izhodno impedanco. Struktura uporablja princip premikanja napetostnega nivoja pri PMOS tranzistorjih. Odlična učinkovitost je bila pokazana tudi s SPICE simulacijami pri pasovni širini 11 GHz, z uporabo zunanega kondenzatorja pri vhodnem toku 200 μ A.

Ključne besede: PMOS premikanja nivoja; nizka napetost; tokovno zrcalo; tokovni način; diferencialen par

*Corresponding Author's e-mail: hamdiercan@erciyes.edu.tr;

1 Introduction

Nowadays, integrated circuit design has concentrated on a circuit with low-voltage operation, low-power dissipation, wide bandwidth and minimum area requirements. A growing need has emerged associated with low-voltage analog circuit design. The demand for circuits operating at low voltage has increased due to the need for low power dissipation. The low-voltage and low-power designs have increased operation time between the battery recharging cycle and have utilized a smaller or lighter-weight battery. Numerous low voltage applications have been proposed earlier [1,2]. Considering several technologies such as bipolar junction transistor (BJT), metal-oxide-semiconductor (MOS) and bipolar complementary MOS (BiCMOS), the CMOS technology has played a crucial role in the development of low power circuit for diverse applications.

The current mirror has been known as a circuit having two terminals whose output current is independent of the output voltage and depends only on the input current. These circuits copying the current carry out a significant function for active elements such as Op-Amp, OTA, current conveyor etc. The low-voltage current mirror has been used in a lot of active elements designed with low-power. The performance parameters of current mirrors like active elements parameters contain linearity, power dissipation, minimum supply voltage requirement, input and output resistance in these applications. At the same time, many active elements include differential pairs designed using PMOS current mirror as an active load [3-6]. The low-voltage operation of the active elements has been restricted because these current mirrors have high input voltage. A low voltage level shifter-based current mirror has been presented in Ref. [7] for current sensor application. Ac-

According to this study, the bandwidth of the circuit was a few tens of MHz. Though this current mirror can be used in low voltage design, the level shifter approach has been designed using only the NMOS current mirror. The threshold voltage of the PMOS transistor is always higher than that of the NMOS. Thus, the circuit presented in Ref. [7] cannot be obtained using a PMOS transistor. However, this case has been resolved by using the proposed circuit.

In the present study, a low-voltage PMOS current mirror employing voltage level-shifting principle has been introduced. The voltage level-shifting operation has been achieved by using bulk voltage in this structure. The circuit utilizes a voltage level shifter at the input port to achieve the high input voltage swing capability. Thus, it can operate with low power supply voltage and low input /low output voltage requirements. Additionally, the proposed structure as an active load has been used in the transconductance amplifier.

2 Conventional PMOS current mirror

A conventional PMOS current mirror (CM) circuit is shown in Figure 1. Transistor M_1 has been used as a diode and the input current copied to output has been compelled to pump by the input voltage.




Figure 1: A conventional PMOS current mirror.

Transistor M_1 shown in Figure 1, operates in saturation mode. Besides, the input impedance of the CM depends on the transconductance (g_m) of the M_1 . The input voltage of the circuit can be written as below:

$$V_{in} = V_{DD} - \sqrt{\frac{2I_{in}}{k_p \left(\frac{W_1}{L_1}\right)}} - V_{THP} \quad (1)$$

where $k_p = \mu_p C_{ox}$ is the conduction factor, V_{THP} is the threshold voltage for PMOS transistor, V_{DD} represents

the supply voltage. Also, W and L are the effective transistor width and length. The output voltage requirement of the CM can be given as

$$V_{out,max} \approx V_{DD} - V_{DS2,sat} \quad (2)$$

where $V_{DS,sat}$ is drain-to-source voltage for relevant transistors in the saturation region. One of the drawbacks of the conventional PMOS CM is that input voltage is always greater than the threshold voltage, being a crucial parameter for low-voltage application. The other disadvantage is the low output impedance. Therefore, using this structure is inconvenient in the low voltage. By using the proposed approach, these challenges have been met.

3 PMOS level-shifter current mirror

Figure 2 indicates the PMOS level-shifted current mirror (PMOS LSCM) circuit for low-voltage applications [8]. Transistors M_1 and M_2 are operated in the saturated region ($V_{SD} > V_{SG} - V_{THP}$) in this circuit. Where V_{SD} and V_{SG} are the source-drain voltage and the source-gate voltage for M_1 and M_2 , respectively. Additionally, V_{THP} is the threshold voltage for M_1 and M_2 . Nevertheless, the most convenient mode is the operation of M_3 in sub-threshold region ($V_{GS3} < V_{THN}$). Where V_{GS3} is the gate-source voltage for M_3 and V_{THN} is the threshold voltage for M_3 . Also, M_1 operates in sub-threshold region for low input currents and saturation region for high input currents [9,10].




Figure 2: PMOS level-shifter current mirror.

Threshold voltage can be defined by [11]

$$V_{THN} = V_{THO} + \gamma \left(\sqrt{2|\phi_F| - V_{BS}} - \sqrt{2|\phi_F|} \right) \quad (3)$$

where V_{THN} is the threshold voltage for M_3 , V_{THO} is the zero- V_{BS} value of the threshold voltage, ϕ_F is the surface




Figure 5: Transconductance amplifiers a) conventional, b) proposed.

as 20 nA. Also, V_{bulk} is equal to $-0.5V (V_{SS})$. Comparison of current/voltage characteristics of the current mirrors is illustrated in Figure 6. V_{in} is the input voltage for LVCM is shown in Figure 3. The value of V_{in} is taken as 0V. The I/V characteristic shown in Figure 6 is obtained by changing the supply voltage between 0 mV and 600 mV.

It is clearly shown that the supply voltage of the proposed LVCM requires the lowest value of the supply voltage compared to any other structures. Therefore, the proposed circuit is suitable for low voltage applications. The current transfer characteristic exhibits linear behavior as depicted in Figure 7. However, deviation from linearity occurs for larger value of currents.

The percentage gain error (I_{out} / I_{in}) of the proposed circuit is approximately 0.3 % for $I_{in}=200 \mu A$ as displayed in Figure 8. Whereas, the percentage gain error (I_{out} / I_{in}) of the PMOS LSCM and conventional CM are 0.6 % and 0.9 % for $I_{in}=200 \mu A$, respectively.




Figure 6: Comparison of I / V characteristics of various CMs.




Figure 7: Current transfer characteristics of proposed LVCM.




Figure 8: Current tracking errors of various CMs.

The I-V characteristics of the proposed LVCM at different input currents are illustrated in Figure 9. The output current swing of the LVCM is almost independent on V_{DD} for low output current values. The value of V_{out}

is taken as 0 V ($V_{out} = 0$ V). Considering the output current of the proposed LVCM it can be operated at 0.5 V as shown in Figure 9.




Figure 9: I-V characteristics of the proposed LVCM.

The frequency responses of the current mirrors are indicated in Figure 10.




Figure 10: Comparison of the bandwidth of various CMs.

There is an improvement in the bandwidth when a capacitance (C) is used and the bandwidth is found to be 11 GHz. It is shown that the bandwidth reduces to 5 GHz when the C is not used in the design. It is seen that as the capacity value increases, the bandwidth increases. Also, the capacitance (C) has a value of 100 pF. The bandwidth of the PMOS LSCM and conventional CM are 0.24 GHz and 17.2 GHz, respectively.




Figure 11: Variation of the bandwidth with external capacitor

The capacitance (C) has a value of 100 pF for 11 GHz shown in Figure 11. As the capacitance value decreases, the bandwidth decreases. The bandwidth can be sacrificed to obtain the lower value of capacitance. The temperature effect on gain-bandwidth performance of the LVCM is depicted in Figure 12.




Figure 12: The temperature effect on Gain-Bandwidth performance of the LVCM.

The current gain is about equal to 0.35 dB for 75 °C as shown in Figure 12. Although higher temperature increases the gain of the LVCM the increase is tolerable. The LVCM exhibits temperature-dependent bandwidth characteristics depending on transistors M_3 and M_6 operates in sub-threshold region as shown in Figure 3. The Monte Carlo analysis which is repeated for 30 times is illustrated in Figure 13.




Figure 13: Monte Carlo analysis for Current Gain.

Figure 13 justifies that current gain value has still stable under 20 % random variations in threshold voltages of the transistors. Figure 13 indicates the good performance of the proposed circuit versus mismatches.

Performance comparison of the aforementioned current mirrors is depicted in Table 2.

Table 2: Performance comparison of the CMs.

Parameter	PMOS CM	Level Shifter CM	Proposed LVCM
Power dissipation (μW)	177	67.7	56.6
3 dB BW, $I_{\text{out}} / I_{\text{in}}$ (GHz)	17.2	0.24	11
V_{in} (mV)	512	470	392
R_{in} (K Ω)	2.56	2.35	1.96
R_{out} (K Ω)	69.5	99.3	130
Gain error, $I_{\text{out}} / I_{\text{in}}$ (%)	0.9	0.6	0.3
for supply voltage = ± 0.5 V and input current $I_{\text{in}} = 200 \mu\text{A}$			

When the performance parameters of the CMs are investigated, it is clearly shown that the proposed structure has a lot of advantages compared with the others. Significantly, the proposed circuit's input resistance is much lower than the others, and it is seen that the suggested LVCM's low input voltage is one of the critical advantages. Also, the gain error belonging to currents ($I_{\text{out}} / I_{\text{in}}$) of the proposed circuit is reasonable compared to the other circuits.

The low-voltage transconductance amplifier used the LVCM and the conventional transconductance amplifier is shown in Figure 5. These circuits were simulated for TSMC 0.13 μm technology. The aspect ratios of the transistors are given in Table 1.

The relation between input difference voltage and output current of the transconductance amplifiers is depicted in Figure 14. Also, the supply voltage has been chosen as ± 0.5 V for both amplifiers. The value of I_B shown in Figure 5 is chosen as $50 \mu\text{A}$.




Figure 14: I / V characteristic of the transconductance amplifiers (input difference voltage versus output current)

Conventional transconductance amplifier has not exhibited good performance at low voltage. The circuit

has not strictly operated at ± 0.5 V for the negative values of the output current. It is shown that the proposed circuit is more suitable than the other circuit for low voltage applications. However, a conventional transconductance amplifier can only be operated on minimum supply voltage with ± 0.65 V, while the proposed circuit can be employed for lower voltage.

Figure 15 indicates the power consumptions of the proposed and conventional transconductance amplifiers for different biasing currents (I_B).




Figure 15: Total power dissipation versus biasing currents for circuits.

As seen in Figure 15, the presented circuit consumes lower power than the conventional circuit for diverse biasing currents. The proposed circuit consumes $70 \mu\text{W}$ for $50 \mu\text{A}$ of biasing current. Hence, the suggested circuit is suitable for low-power applications.

The frequency performance of the transconductance amplifiers is illustrated in Figure 16.




Figure 16: The frequency response of the transconductance amplifiers.

Frequency responses of the transconductance (g_m) value for the proposed and conventional circuits are indicated in Figure 16, which gives a bandwidth (-3dB) of 398.8 MHz and 581.1 MHz, respectively.

The total harmonic distortion (THD) is evaluated for input voltage with different amplitudes for a biasing current of 50 μA , as shown in Figure 17.




Figure 17: THD (%) versus input voltage (at a frequency of 1 MHz) for the proposed circuit.

The fundamental frequency (1st harmonic) has been specified and THD has been calculated via the PSpice program. The third harmonic provides the most important contribution to the total harmonic distortion of the circuit. The THD has a value of about 0.94% for 250 mV_{p-p}. It is shown that THD obtained according to the different peak-to-peak input voltages are reasonable values.

6 Conclusion

A low-voltage current mirror circuit employing the voltage level-shifting principle is demonstrated for use in differential pair as an active load. The proposed current mirror operates at $\pm 0.5\text{ V}$ and its bandwidth is about 11 GHz. Also, it consumes 56.6 μW power. The proposed circuit exhibits better performance than the other CMs called PMOS CM and level shifter CM. It is undeniable that the simulation results confirm the validity of the theory and demonstrate the usage of the LVCM in electronic applications. Also, the proposed transconductance amplifier using LVCM has been compared to the conventional one. The proposed transconductance amplifier's bandwidth is about 581.1 MHz. It consumes 70 μW power. Finally, such a current mirror is appropriate for low-voltage applications, resulting in increasing threshold voltage. Hereafter, the suggested PMOS current mirror would be operated even at lower supply voltages if the threshold voltages could be decreased.

7 Conflict of interest

The authors declare no conflict of interest.

8 References

1. S. Chatterjee, Y. Tividis, and P. Kinget, "Ultra-low voltage analog integrated circuits," *IEICE Trans. Electron.*, vol. E89-C, no. 6, pp.673–680, 2006, <https://www.doi.org/10.1093/ietele/e89-c.6.673>.
2. S.A. Tekin, H. Ercan, and M. Alçı, "Novel low voltage CMOS current controlled floating resistor using differential pair," *Radioengineering*, vol. 22, no. 2, pp. 428-433, 2013, <https://dx.doi.org/10.13164/re>
3. H. Ercan, "A linear current-controlled floating negative resistor," *Informacije MIDEM Journal of Microelectronics, Electronic Components and Materials*, vol.43, no.4, pp.222–227, 2013.
4. S.A. Tekin, "Voltage summing current conveyor (VSCC) for oscillator and summing amplifier applications," *Informacije MIDEM Journal of Microelectronics, Electronic Components and Materials*, vol. 44, no. 2, pp. 159–167, 2014.
5. K. K. Abdalla, D. R. Bhaskar and R. Senani, "A review of the evolution of current-mode circuits and techniques and various modern analog circuit building blocks," *Nature & Science*, vol. 10, no. 10, pp. 1–13, 2012, <https://www.doi.org/10.7537/marsnsj101012.01>
6. K. Monfaredi, H. Faraji Baghtash, "An Extremely Low-Voltage and High-Compliance Current Mirror" *Circuits Syst Signal Process*, vol. 39, pp. 30–53, 2020, <https://doi.org/10.1007/s00034-019-01175-1>.
7. J. Ramirez-Angulo, "Low voltage current mirrors for built-in current sensors," *IEEE International Symposium on Circuits and Systems ISCAS '94*, vol. 5, 1994, pp. 673–680, <https://www.doi.org/10.1109/ISCAS.1994.409429>.
8. H. Ercan, S.A. Tekin, and M. Alçı, "Low-voltage low-power multifunction current-controlled conveyor," *International Journal of Electronics*, vol. 102, no. 3, pp. 444–461, 2015, <https://doi.org/10.1080/00207217.2014.897382>.
9. S.S. Rajput, and S.S. Jamuar, "A current mirror for low voltage, high performance analog circuits," *Analog Integrated Circuits and Signal Processing*, vol. 36, no. 3, pp.221–233, 2003, <https://doi.org/10.1023/A:1024718421282>.

10. S. Yan, and E. Sanchez-Sinencio. "Low voltage analog circuit design techniques: A tutorial," *IEICE Transactions on Fundamentals of Electronics, Communications and Computer Sciences*, vol.83, no.2, pp. 179–196, 2000.
11. A. S. Sedra and K. C. Smith, *Microelectronic Circuits*, Revised Edition, Oxford University Press, New York, 2007.



Copyright © 2021 by the Authors.
This is an open access article distributed under the Creative Commons Attribution (CC BY) License (<https://creativecommons.org/licenses/by/4.0/>), which permits unrestricted use, distribution, and reproduction in any medium, provided the original work is properly cited.

Arrived: 11. 01. 2021

Accepted: 01. 04. 2021